

AD-LC 3 LED DRIVER



AD-LC3 RGB-LED driver

- 4 channel high-power LED driver
100 Watt each channel, total output 320 Watts
- DMX-512-1990 input
- Four analogue 0...10V / 1...10V control inputs
- RS485/RS232 A/V interface (Domotica)
- Smooth brightness control (SmartWave™)
- 4 high-current (14 Amp) fully protected output stages with short-circuit, over-temperature, over-voltage and over-current protections
- Controllable refresh rate (up to 800 Hz) for Studio applications
- Stand alone modes with 16 build-in programs and controllable speed
- Several control options
- Menu controlled user interface
- EASY installation with DIN rail mounting

Specifications:

Power supply:	10~24 VDC
Output power	320 Watt max. (max 100 Watts / channel)
Dimensions:	75 x 55 x 110 mm
Weight:	278 g

■



WWW.RGB-LED.NL